



Compact 4-in-1 mono laser printer MFC-L2710DW











PRINT

COPY

SCA

WIRELESS

www.brother.eu

Compact 4-in-1 mono laser printer

The MFC-L2710DW is ideal for the busy home and small office. This simple to use and easy to setup device, provides professional quality prints, together with built-in wired and wireless connectivity for printing from mobile phones and tablets.

MFC-L2710DW



Key Features:

- Fast print speeds of up to 30 pages per minute
- Automatic 2-sided print
- 250 sheet paper input
- 50 sheet Auto Document Feeder
- Built in wired and wireless connectivity
- Up to 700 Page* inbox toner
- 64MB memory

Performance designed for businesses of tomorrow

Successor to the BLI Pick Award winning 'MFC-L2700DW', the MFC-L2710DW is designed to be set-up and ready to be used in minutes. Compact, and desktop friendly. You can enjoy fast print speeds up to 30 pages per minute, and a large 50 sheet automatic document feeder, for multi-page copying and scanning. Easily share documents, by scanning and sending directly via email, or save to SharePoint and other destinations.

Maximum value for money

The wireless MFC-L2710DW, comes with a host of cost saving elements, including, automatic 2-sided printing, and high yield toner cartridges reduces the cost of each print job.

Quiet without compromise

Print quietly without comprising on speed or quality, operating at the lowest decibel in class (under 50dB). This desktop friendly printer, can sit on your desk, printing quietly at full speed in the background, while you work.

Designed to go the distance

Built to perform for longer. The MFC-L2710DW, has been designed with you in mind. Made from robust and hardwearing materials and supported by outstanding service as standard, providing the peace of mind that your printer will keep on going.



General

Technology

Electrophotographic Laser Printer

Laser Classification

Class 1 Laser Product (IEC60825-1:2014)

Processor 600MHz

Memory 64MB

Wired Network Interface

10Base-T/100Base-TX

Wireless Network

IEEE 802.11b/g/n

Control Panel

2 Line, 16 character LCD Display

Local Interface

Hi-Speed USB 2.0

Print

Print Speed Standard (A4)

Up to 30ppm (pages per minute)

Print Speed 2-Sided (A4)

Up to 15 sides per minute (8 sheets per minute)

Resolution

Up to 1,200 x 1,200dpi

Quiet Mode

A mode to reduce the printing noise by reducing the print speed to 13ppm

Automatic 2-Sided Printing

Print on to both sides of the paper

FPOT (First Print Out Time)

Less than 8.5 seconds from ready mode

Warm Up Time

Less than 9 seconds from sleep mode

Print Languages

GDI

Printer Functions

N-up Printing³

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)

Poster Printing⁴

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

Watermark Printing⁴

Watermark your documents with predefined text or with your own user-defined messages

ID Printing⁴

Add identification to your printed documents (date & time, short custom message or PC username)

Manual 2-Sided Print4

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

Booklet Printing⁴

Print documents in A5 booklet format using automatic or manual 2-sided print

Print Profiles³

Store your favourite driver settings as profiles to easily recall them

Print Text In Black4

Converts all text in your documents to black when printed

Print Archive⁴

An electronic carbon copy feature that saves an electronic copy of all printed documents as a PDF file

Printer Driver

Windows®

Windows® 10 (32 & 64 bit editions) Windows® 8 (32 & 64 bit editions) Windows® 7 (32 & 64 bit editions) Windows® Server 2016 (32 & 64 bit editions)* Windows® Server 2012, 2012R2 & 2008R2* Windows® Server 2008 (32 & 64 bit editions)*

Macintosh⁵

macOS 10.8.x or greater

Linux⁵

CUPS, LPD/LPRng (32 & 64 bit editions)

* Windows® Server supports network printing only

¹ Approx declared vield value in accordance with ISO/IEC 19752.

² Calculated with 80g/m² paper.

³ Windows® & Mac® only.

⁴ Windows® only. 5 Optional download.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

⁷ Requires Brother software.

Standard Paper Handling

Paper Input²

Standard Tray - 250 sheets Manual feed slot - 1 sheet

Automatic Document

Feeder (ADF) – 50 Sheets

Paper Output²

Face Down - 120 sheets Face Up (Straight Paper Path) - 1 sheet

Media Specification

Media Types & Weights Standard

Plain & recycled paper (between 60 - 163g/m²)

Manual feed slot

Plain, Recycled, Bond, Label, Envelope, (between 60 - 230g/m²)

2-sided Print

Plain & recycled paper (between 60 - 105g/m²)

Envelope & Label Printing

Yes, from the Manual feel slot: support for 1 envelope / sheet

Media Sizes Standard Tray

A4, Letter, A5, A5 (Long Edge), A6, Executive Manual feed slot

Width: 76.2mm to 215.9mm x Length: 127mm to 355.6mm

2-sided Print

A4

Mobile / Web Based Printing & Scanning

Brother iPrint&Scan (Android)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device

Brother iPrint&Scan (iPad / iPhone / iPod)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an iPad / iPhone / iPod Touch

Brother iPrint&Scan (Windows® Phone)

Print from and scan to a smart phone running the Windows® Phone Operating System

Brother Print&Scan (Windows® 8,10 & RT)

Print from and scan to a Windows® 8,10 or Windows RT Tablet

Google Cloud Print 2.0

Print most common file types from any Google Cloud Print enabled application

Apple AirPrint

Print from and scan to most common file types from any AirPrint enabled application

Brother Print Service Plugin

Print from Android devices without a dedicated App

Mopria

Print most common file types from Mopria supported Android devices

Copy

Speed - (A4)

Up to 30cpm (copies per minute)

FCOT (First Copy Time Out)

Less than 10 seconds from ready mode

Resolution

Up to 600 x 600dpi

Multi-Copying/Stack/Sort

Makes up to 99 copies of each page / Stacks or Sorts

Enlargement/Reduction Ratio

Reduce or Increase document sizes from 25% to 400% in 1% increments

N in 1 Copying

Allows the user to compress 2 or 4 pages on to a single A4 sheet

2in1 ID Copying

Allows the user to copy both sides of an ID card to a single A4 sheet

Grey Scale

256 shades of grey (8 bit)

Receipt Copying

Produces clearer copies of receipts

¹ Approx declared yield value in accordance with ISO/IEC 19752.

² Calculated with 80g/m² paper.

³ Windows® & Mac® only.

⁴ Windows® only.

⁵ Optional download.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

⁷ Requires Brother software.

Scan

Scanner Type

CIS (Contact Image Sensor)

Colour & Mono Scanning

Yes

Scan Speed Mono

23.6ipm (images per minute)

Scan Speed Colour

7.5ipm (images per minute)

Scan Resolution from ADF

Up to 600 x 600dpi

Scan Resolution from Scanner Glass

Up to 1,200 x 1,200dpi

Interpolated Scan Resolution

Up to 19,200 x 19,200dpi

Colour Depth

16,777,216 colour variations (24 bit)

Grey Scale

256 shades of grey (8 bit)

Standard Functions⁷

Scan to E-mail, OCR, Image & File

Scan Features

Remove Background, Skip Blank Page⁴, ID Scan⁴, 1 to 2 Scan⁴, Split PDF

Scan to SharePoint^{4&7}

Scan documents directly into SharePoint

Windows® Web Services Scanning

Scan direct into Windows® (from Windows® 7 & onwards) without needing to install a scanner driver

Scanner Driver

Windows®

TWAIN & WIA
Windows® 10
(32 & 64 bit editions)
Windows® 8.1
(32 & 64 bit editions)
Windows® 8
(32 & 64 bit editions)

Macintosh⁵

TWAIN & AirPrint macOS 10.8.x or greater

Linux⁵

SANE(32 & 64 bit editions)

Fleet Management Tools

Unattended Installer4

Ability to centrally deploy and customise our drivers and software

MSI Installer4

Modular installers that can be distributed through Active Directory®

BRAdmin Light^{4&5}

LAN/WAN management software

Embedded Web Server

Web based print management software embedded onto the device

Driver Deployment Wizard⁴

Easily create print drivers for hassle free deployment over your network

PrintSmart Solutions (optional)

PrintSmart Cost Control

Monitor and control printing costs for all Brother and 3rd party devices

For more information on PrintSmart Solutions visit: **www.brother.eu**

Address Book

Speed Dials

200 locations for E-mail addresses and fax numbers

Group Dial

A combination of up to 20 groups can be stored for broadcasting

¹ Approx declared yield value in accordance with ISO/IEC 19752.

² Calculated with 80g/m² paper.

³ Windows® & Mac® only.

⁴ Windows® only.

⁵ Optional download.

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

⁷ Requires Brother software.

Network and Security

Wired Network

Built in Ethernet 10Base-T/100Base-TX

Network Protocols

TCP/IP (IPv4 and IPv6)

Wired Network Security

SMTP-AUTH, SNMP v3,SSL/ TLS(SMTP,HTTP,IPP)

Wireless Network

IEEE 802.11b/g/n (Infrastructure Mode / Adhoc Mode)

Wireless Set-Up Support

Wi-Fi Protected Setup (WPS)

Wireless Applications

Vertical Pairing

IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/IPPS, FTP Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print), SNTP Client

IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Server, SNMPv1/v2c/v3, HTTP/ HTTPS server, TFTP client and server, ICMPv6, SNTP Client. Web Services (Print)

E-mail Notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail Reports

Receive usage reports on a regular basis via e-mail

IP Filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

Setting Lock

Secures access to the devices control panel by locking it

Supplies

Inbox Toner

700 pages¹

Standard Yield Toner

1,200 pages¹ (TN-2410)

High Yield Toner

3,000 pages¹ (TN-2420)

Drum (DR-2400)

Approx 12,000 pages

Carton Contents

Toner cartridge, drum, power supply cord, driver software for Windows®, Quick Set-Up Guide (PC interface cable NOT included)

The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.

Dimensions and Weights

Without Carton (WxDxH)

410 x 398.5 x 318.5 mm -11.8kg

With Carton (WxDxH)

580 x 517 x 434 mm - 14.7kg

Duty Cycles

Recommended Monthly

Up to 2,000 pages monthly print volume

Maximum Monthly⁶

Up to 15,000 pages monthly print volume

7 Requires Brother software.

¹ Approx declared yield value in accordance with ISO/IEC 19752.

² Calculated with 80g/m² paper.

³ Windows® & Mac® only.

⁴ Windows® only.

⁵ Optional download

⁶ Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

Environment

Power Consumption

Printing - 440W (260W in quiet mode), Ready - 42W,

Sleep - 6.2W, Deep sleep - 0.6W,

Off - 0.03W

TEC Value

1.232kWh / Week

Sound Pressure Level

Printing 48dbA, Quiet mode printing 44dbA, Ready Up to 30dbA

Power Saving

This enables the printer to consume less energy when not in use

Toner Saving

This reduces the toner usage and helps to reduce the total cost of printer ownership

Blue Angel

Yes

Nordic Swan

Yes

GS Mark

Yes

Eco Mode

Yes

Fax

Fax Modem

33,600bps (Super G3)

PC Fax Send^{9&3}

Send faxes directly from your PC

PC Fax Receive9&4

Receive faxes directly to your PC

Automatic Redial

Automatic redialling if the recipient fax is busy

Telephone Index

An electronic, alphabetical listing of stored speed dials and group numbers

Chain Dialling

Allows the user to store parts for long dialling sequences in different speed dial locations

Distinctive Ring Detection (UK & Denmark only)

An external service that allows two or more telephone numbers shared on a single fixed line and use different ring tones

Speaker / Ring Volume

3 levels and off

Fax / Tel Switch

Automatic recognition of fax and telephone reception

Super Fine

Enables quality transmission of very small print and line drawings

Contrast

Auto / light / dark

Enhanced Remote Activate

Transfer a fax call, answered on an extension phone, to the fax machine

Delayed Timer

Up to 50

Quick-Scan

Approximately 2.5 seconds per page A4 standard resolution

Memory Transmission

Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)

Out of Paper Reception

Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)

Dual Access

Send the same fax message to up to 250 separate locations (manual 50 locations)

Broadcasting

Receive usage reports on a regular basis via e-mail

Auto Reduction

When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet

ECM

(Error Correction Mode)

The MFC will detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)

Fax Forwarding

Sends a fax received in memory to another pre-programmed fax number

Remote Access

Allows users to remotely access their machine

Fax Retrieval

Allows remote access to faxes stored in the machine

Remote Maintenance

Allows users to maintain their MFC remotely

Remote Set-Up³

Allows users to set-up the MFC from their PC

Grey Scale

256 shades (8 bit) of grey are available for faxing

Fax Stamp

Add the date and time to all received faxes

Cover Page

Create custom cover pages for outgoing faxes

- 1 Approx declared yield value in accordance with ISO/IEC 19752.
- 2 Calculated with 80g/m² paper.
- 3 Windows® & Mac® only
- 4 Windows® only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.
- 7 Requires Brother software.























Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

